

## PCI-EXPRESS

- Single-slot 32 bit PCI Express module
- IRIG A, B, NASA 36, 1 PPS sync inputs
- GPS sync option (maintains single-slot)
- HaveQuick sync input option
- Propagation delay correction
- Zero latency time reads
- Match Time output
- IRIG-B time code output (option)
- External Event time tags
- Three user programmable rates



The PCI-Express from Brandywine Communications provides precision time with zero latency to the host computer through a PCI Express X1,X2,X4,X8,X16 or X32 slot. An on-board microprocessor automatically synchronizes the clock to reference signal inputs. The reference signal inputs can be 1 PPS, IRIG or NASA time codes and optionally, GPS or HaveQuick. The clock can free run and be set by commands from the host over the PCI Express bus.

The on-board clock accepts an IRIG A, B, or NASA 36 input and accepts user input reference input signal delay information. An IRIG B code generator is available.

The advanced microprocessor on the PCI-Express module constantly measures the time error between the on-board clock and the reference input code and adjusts the error measurement for propagation delay. In units with a disciplined TCXO or OCXO the residual error is used in an adaptive gain loop to adjust the frequency of the oscillator for minimum error. If the incoming time code is missing, or corrupted by noise, the on-board clock is updated using the disciplined oscillator. When the input code is again useable the correction loop is smoothly closed.

58 bits of BCD time data are available to the host computer using two zero latency time reads. The time message contains units of microseconds through units of years. A status word is available using an additional read.

The exact time-of-occurrence of random external events may be captured by using the Event Time input. When the event input is sensed the current time is saved in a buffer for later interrogation by the host. The resolution of the time tag is 100 nanoseconds.

Internal or external processes may be automatically initiated or terminated by using the Match Time feature. This feature asserts an output when the clock's time matches that of the user input start time. The output is terminated under user control or when the pre-programmed stop time is encountered. The resolution of the Match Time comparison is one microsecond.

Three user programmable pulse rates are provided. Two pulse rates, Clock Low and Clock High, are available on the multi-pin connector. The third rate generator provides heartbeat timing to the host. The divider for each of the three rate generators is programmable by the host over the range 2–65,535. The inputs to the rate generators are 3 MHz or 100 Hz for the heartbeat, 3 MHz for Clock High and 100 Hz for Clock Low.

The GPS synchronization option adds worldwide time transfer capability that can be traced to the U.S. Government standard UTC-USNO. Very precise synchronization, automatic leap year and leap second correction, and accurate position information are additional benefits provided by the GPS option.

Software packages for Windows, VxWorks and Linux are available. C language samples are supplied with the PCI-Express.

In addition to the comprehensive set of standard capabilities of the PCI-Express, Brandywine Communications offers a wide range of options that may be specified. These options allow the user to customize the PCI-Express to fit almost any application.

# brandywine communications

## PCI-Express Specifications

### General Input Specifications

Input Codes	IRIG A & B, NASA 36 (1kHz Carrier)
Input Amplitude	.25 to 10 Vpp
Input Impedance	>10k Ohms
Ratio	2:1 to 6:1
Frequency Error	100 PPM maximum
Code Sync Accuracy	One microsecond
1PPS Input	TTL, positive edge
1PPS Sync Accuracy	One microsecond
External Event	TTL, positive or negative edge
Resolution	100 nanoseconds–units of year
Min. event spacing	None

### General Output Specifications

IRIG B DC Shift	TTL (Option)
Match Pulse	TTL level toggles at Match time
Resolution	Microsecond
Clock Low Rate	TTL, negative going pulse
Clock Divisor	2–65,535
Clock Input	100 PPS
Default output	1 PPS
Clock High Rate	TTL, negative going pulse
Clock Divisor	2–65,535
Clock Input	3 MPPS
Default output	76.923k PPS
Heartbeat Rate	Interrupt, flag and TTL, negative going pulse
Clock Divisor	2–65,535
Clock Input	100 PPS or 3 MPPS
Default output	1k PPS
BCD Time	Microseconds–unit year on demand, zero latency 58 bits in two 32 bit words
Status word	8 bits
Status LED	Flashes coded patterns
Interrupts	External Event, RAM FIFO, Heartbeat, Match Time
Flags	Dual Port RAM data ready, FIFO data ready, In sync, Heartbeat, Match Time, External Event
Connectors	BNC, high density DB-26
<b>MTBF</b>	155,000 Hours Per MIL 217 F, Notice 2, at 25°C

### Mechanical & Environmental

Size	107mm X 175mm (PCI Express Half Length)
Type	Single-slot X1 PCI-Express
Power	
+12 Vdc	±5%, 300 mA typ 750mA max
+3.3 Vdc	±10%, 100 mA typ, 150mA max
Operating Temperature	0°C to +70°C
Storage Temperature	-40°C to +85°C
Humidity	To 95% without condensation

### Options

GPS Sync Input	C/A code
Sync Accuracy	100 nanoseconds
Position Accuracy	25 meters SEP
Tracking	Eight parallel channels
Antenna	L1 magnetic mount, 25' cable
Antenna Options	
Hi-gain	L1, mast mount, 100' cable
Fiber Optic Kit	Fiber optic transmitter-receiver pair for long antenna cable runs Per RTCM 104
Differential GPS Inputs	Transformer coupling
IRIG B Modulated Output	IRIG G, XR3, 2137, IRIG E, 109-60
Input Code Isolation	IRIG A, NASA 36, IRIG G
Input Codes	TTL positive or negative edge
Output codes	Per ICD–GPS–060
Eight External Event Inputs	Per ICD–GPS–060
Have Quick Input	Replaces BCD
Have Quick Output	Disciplined TCXO, 1 PPM
Binary Time Words	Disciplined OCXO, .01 PPM
Oscillator Upgrades	Sync input, +10 Vdc, 50 ohms
1 PPS 10 Vdc input	Time code sync input
STANAG 4430	Time code output
STANAG 4430	TTL
IRIG B D.C. shift time code	Windows, Linux, VX Works
Software packages	

### Other **brandywine communications** :ts

- Master Clocks and Modular Timing Systems
- GPS Synchronized Clocks
- PCI, VME, PMC, PC/104, CPCI, ISA Computer Clock Synchronization Boards
- Network Time Servers
- Frequency Generation and Distribution Instruments
- Dual & Triple Redundant Systems
- Time and Message Displays

© brandywine communications 02/24/2010